

- 1) IRRIGATION CONTROLLER:
  RAIN BIRD IQ ESP-LXME SATELLITE CONTROLLER WITH IQ NCC
  ETHERNET CARTRIDGE IN LXMM METAL CABINET WITH OUTSIDE WALL
  MOUNT. INSTALL CONTROLLER AND CABINET ON WALL PER
  MANUFACTURER'S RECOMMENDATIONS.
- (2) JUNCTION BOX
- (3)1-INCH CONDUIT AND FITTINGS TO POWER SUPPLY
- (4) POWER SUPPLY WIRE
- (5) 1-INCH CONDUIT AND FITTINGS FOR ETHERNET SERVICE TO IQ CENTRAL CONTROL COMPUTER
- (6) ETHERNET CABLE TO LOCAL NETWORK JACK FOR COMMUNICATION TO IQ CENTRAL CONTROL COMPUTER (MAXIMUM LENGTH 300 FEET)
- $\overline{7}$ ) 2-Inch conduit and fittings for station wires
- (8) WIRES TO REMOTE CONTROL VALVES

## NOTES:

- 1. IQ ESP-LXME CONTROLLER IS AVAILABLE IN 8- OR 12-STATION BASE MODELS. ADDITIONAL MODULES IN 4-, 8- AND 12-STATION VERSIONS MAY BE ADDED TO BRING THE CONTROLLER UP TO 48 STATIONS MAXIMUM.
- 2. FOR EASE OF INSTALLATION INTO A CONTROLLER WITH MORE THAN 24 STATIONS, INSTALL A JUNCTION BOX AT THE BASE OF CONTROLLER AND TRANSITION LARGER VALVE AND COMMON WIRES FROM FIELD TO 18 AWG MULTI CONDUCTOR WIRE TO BE USED IN CONTROLLER.
- 3. USE STEEL CONDUIT FOR ABOVE GRADE AND SCH 40 PVC CONDUIT FOR BELOW GRADE CONDITIONS.
- 4. PROVIDE PROPER GROUNDING COMPONENTS TO ACHIEVE GROUND RESISTANCE OF 10 OHMS OR LESS.



## IQ ESP-LXME SATELLITE CONTROLLER WITH IQ NCC ETHERNET CARTRIDGE

1 - 11 - 11

N.T.S.

IN METAL CABINET